

2 and 4 Button VOYAGER VOICE GSM Intercom



- **Bright Display of Residents Names**
- **Female Spoken Voice**
- **Control 2 Gates or Doors**
- **IP55 Waterproof Housing**
- **3 Call Out Numbers Per Button**
- **200 Call In Numbers**
- **Automated Schedules**
- **Do Not Disturb Mode, Back Light**
- **Downloadable Log**
- **Programming Security Code**
- **Free Installer & End User App**



Operating Bands
Power

4G, 3G and 2G GSM bands
12V DC 2 Amp (supplied)

Call Out Phone Numbers
Dial to Open users

3 per Button
200

Keypad Operation

10 x 4 Digit codes for any number of users.
24 x 7 Or Time and Day limited Codes
Temporary Lifetime Code available
Remove, List & Configure all codes

Method of programming.
Method of operation.

Mobile Phone App, Android & IOS
- Press the intercom call panel
- Dial to open (no call cost) and SMS text
- Enter 4 digit pre configured Keypad code

Pulse Time
Gate open for fixed period

3 seconds (Configurable).
SMS command or App. Programmable time period. From a minute to many hours.

Security Settings

4 Digit security code can be applied to all SMS Text.

Number of Inputs
SMS Text on gate open/close
Gate Status

2
Control Phone or Phone 1
SMS text to query if gate open.

Keeps SIM on the network

Text sent by device to Control Phone or Phone 1, every 30 days to add credit.

Automatic Schedules for
Output 1 or Output 2
Out of Hours Schedule Programmable.

10 schedules that can be specified by day and time. It can be specified with a limited lifetime if required.



2 & 4 Button VOYAGER VOICE GSM Intercom

External Dimensions

